

Accuracy and tracking performance extremely improved

# Radar Level Transmitter



MWLM-PR26 Series




# Extended the product warr

Matsushima's radar level transmitter is manufactured domestically from software to hardware, so it can be delivered quickly with stable supply, and also support our customers with quick maintenance. Since Matshushima has 60 years of experience in measurement control, we are able to meet our customer's requests regarding installation to the facilities.


## **Customization**

Customize the level meter for suitable measuring environments and usage. Able to provide customized level meter in applications that have restrictions under high temperature and high pressure areas.



## **Measuring Principle**

The microwave level meter measures the time from when the level meter emits pulse radar waves from the antenna to when the waves (echoes) reflected from the object to be measured return to the meter, which is then calculated into a distance.



## Explosion-proof type Intrinsically safe construction Ex ia II B T4 X (TIIS) non-hazardous area hazardous area Zone1 DC20~32V Power supply Zon0. Output Zone1 Zone2 DC4~20mA Intrinsic Safety type Safety barrier Radar Transmitter KFD2-STC4-Ex1 MWLM-PR26H7SEx

# anty period to 2 years.




## **Applications**

Applies to a variety of applications and flexible customization capability based on our long experience and know-how.

## Usage in Applications




If there's no space to install on top of the silo, it is able to measure from the side of the silo




By attaching the PTFE antenna, it is able to measure corrosive chemicals.




Narrow beam angle allows to measure inside a thin, long grain silos.




Able to continuously measure without being affected by rain, wind, and snow.



Even if antenna is not allowed to be put inside, it can be measured by flat antenna type.



It can follow a sudden level change in bunker. Dust and vapor do not influence level measurement.



It is suitable for vertial shaft or crusher due to high tracking-speed performance.





The liquid level can be measured without foam intrusion into piping.

## Material to be eaily built up



PTFE coating antenna prevents the material from being built up on the antenna, and results in stable level measurement.





## **Easy Operation**


Simple and precise operation possible. Site maintenance with simple hand communicator "GRAPHIC COM4". Remote operation with customer friendly software.

Local Operation "GRAPHIC COM4", a detachable LCD adjuster, has a liquid crystal display with high-visibility. You can see waveforms in real time while monitoring, and you can adjust settings if needed.


Remote Operation The PC with adjustment software allows easy operation for complex parameter settings.



GRAPHIC COM4 on the sensor head



Real time indication for measurement situation





### Software Features

- · Real time indication for measurement situation
- · Make adjustment
- · Check waveforms while monitoring and store the data
- · Record trends
- · Languages: Japanese, English, Chinese, and Korean



## High measuring performance under any conditions

## ①Improved accuarcy

Double measuring accuracy!

Model	Before	New version	
For powder H7.H3	±50mm	≦1.2m: ±20mm >1.2m: ±10mm	
For liquid H2、H1、C1	±50mm	≦1.2m: ±30mm >1.2m: ±20mm	

## 2 Improved tracking speed

Faster response time & better tracking performance than Ultrasonic sensor

10

11.2s

9.0s

9.0s

6.2s

Radar (former version)

5.2s

2.6s

Radar (new version)

6.10m | Measuring distance(m)

Measuring distance(m)

\*Response time depends on measuring distance & adjustments

## ③Expanded allowable power supply

Reliable under unstable power circumstances where voltage fluctuates

LCD display	Before	New version
No LCD	DC20~32V	DC13~36V
With LCD	DC20~32V	DC16~36V

Remark: 20 -32V for Ex-proof type

## Wiring distance increased

Load resistance has improved from 499  $\!\Omega$  to 655  $\!\Omega!!$  Max. wiring distance extended.

	Before	New version
Max. wiring distance	4.5km	7.5km

Conditions: Power supply DC24V, Load resistance  $250\Omega,$  Cable (AWG#18, dia.0.75mm, Load resistance  $26\Omega/\text{km})$ 

For Liq	uid	Specifications					
Model		MWLM-PR26C* MWLM-PR26H*					
Product Code		MWLM-PR26C1G*	MWLM-PR26H1G	MWLM-PR26H2G*	MWLM-PR26H2F*		
Antenna		Cone	Horn				
Power Sup	nlv	Standard: DC13 - 36V *1 DC16V or more is required for LCD unit.					
Fower Sup	piy	Ex-proof: D	C20 - 32V*2 Power supplied	by safety barrier KFD2-STC4-E	Ex1		
Power Con	sumption	Standard type: Approx. 704mW, Explosion-proof: Approx. 540mW					
Mounting		G2 Thread	G1 Thread	G1 1/2 Thread	JIS5K50A Flange		
Dead Zone			0.5m (1.64ft) be	low the antenna			
Max Measu	rable Distance	10.0 m (33ft) from measu	ıring reference zero point	20.0 m (66ft) from measu	uring reference zero point		
Transmitting	g Frequency		Approx.				
Transmitting	g Cycle		Every	83ms			
Beam Angle	e	Approx. 24° (approx. 48d	leg. including side beam)	Approx. 18° (approx. 36c	deg. including side beam)		
Resolution		1mm					
Allowable Fl	uctuation Rate			m/s			
Accuracy	Repeatability	Within 1.2m (3.94ft) or less: ±30mm (1.18in), Over 1.2m (3.94ft) or more: ±20mm (0.78in) or ±0.04% of measurement range (Whichever is greater)					
Accuracy	Temp. Error	Standard: ± 0.03% /10K, Ex-proof: 0.06%/6K					
Ambient	Housing	Standard: $-40 \sim +80^{\circ}\text{C}$ ( $-40 \sim +176^{\circ}\text{F}$ ), With LCD: $-20 \sim +60^{\circ}\text{C}$ ( $-4 \sim +140^{\circ}\text{F}$ ), Ex-proof: $-20 \sim +50^{\circ}\text{C}$ ( $-4 \sim +122^{\circ}\text{F}$ )					
Temperature		1 hour is required to warm up the device if the temperature is lower than -20℃ (-4℉).					
	Antenna			, Ex-proof: -40 $\sim$ +100 $^{\circ}$ C (-40 $\sim$			
Allowable F		500kPa	500kPa 1MPa 490ki				
Material	Housing		AC				
	Antenna	PTFE	SUS304	SUS	316L		
Protection		IP67 (Housing cover and lead outlet must be closed)					
Lead Outle		1-G1/2 (Applicable cable size: ∮8 to 12mm (0.31 to 0.47in)					
Output Sign		DC4 $\sim$ 20mA $\times$ 1 (Load resistance when 24VDC power supply is used; 499 $\Omega$ max), HART communication					
Integral Time			0~!				
Mass		Approx. 1.9kg	Approx. 1.6kg	Approx. 1.9kg	Approx. 2.2kg		
Explosion-proof		Intrinsically safe construction					
construction		Ex ia II B T4 X (TIIS)	Ex ia II B T4 X (TIIS)				
Division of hazadous	Housing		Zone1, Zone2 –		Zone1, Zone2		
section	Antenna	Zone1, Zone2	_	Zone0, Zone1, Zone2			
Accessories (option)  LCD adjustment unit (GRAPHIC COM4) · Data Communication cable (MHM-01) · PC adjustment softw Safety barrier (KFD2-STC4-Ex1) is needed to use the explosion proof type. LCD display can't be used since it's a n							

H2G

★: Explosion Proof model has Ex written at the end of each model. Explosion proof structure is Ex ia IB T4 (TIIS).

## Dimension mm [in]




B 4×φ15 [0.59"] Mounting hole


C 8×\$\psi\$19 [0.75"] Mounting hole D Earth terminal (M4)


F Purge nozzle: Rc1/8 G Measurement reference zero poin

E Housing



(262) [(267)] (262) (267) [(261)] (262) (267) [(267)] (262) (267) [(2	(405) [15.94"]	[150 [5.91"] (255) [10.04"]	
Cable: $\phi$ 8-12mm [0.31-0.47"]	ı		
	ì		
	ı		
Be sure to ground the earth terminal. (D-class grounding)	ì		
Housing rotatable in 310°.	ı		
	1		








For Pov	wder	Specifications					
Model				MWLM-	PR26H*		
Product Code		MWLM-PR26H3G*	MWLM-PR26H3F*	MWLM-PR26H3S*	MWLM-PR26H7G*	MWLM-PR26H7F*	MWLM-PR26H7S*
Antenna				He	orn		
Bower Sup	nlv	Standard: DC13 - 36V *1 DC16V or more is required for LCD unit.					
Power Supply		Ex-proof: DC20 - 32V*2 Power supplied by safety barrier KFD2-STC4-Ex1					
Power Con:	sumption	Standard type: Approx.704mW, Explosion-proof: Approx.540mW					
Mounting		G1 1/2 Thread	JIS5K65A Flange	Swivelling Flange (Equivalent to JIS10K100A)	G1 1/2 Thread	Equivalent to JIS10K100A	Swivelling Flange (Equivalent to JIS10K100A)
Dead Zone				0.3m (0.98ft) be	low the antenna		
Max Measur	rable Distance	35.0m (115ft)	from measuring referer	nce zero point	70.0 m (330ft	) from measuring refere	nce zero point
Transmitting	g Frequency			Approx	. 26GHz		
Transmitting	g Cycle			Every	83ms		
Beam Angle	е	Approx. 14deg	. (approx. 28deg. includ	ling side beam)	Approx. 8deg	. (approx. 16deg. includ	ling side beam)
Resolution		1mm					
Allowable Flu	uctuation Rate				:m/s		
Accuracy	Repeatability	Within 1.2m (3.94ft) or less: ±30mm (1.18in), Over 1.2m (3.94ft) or more: ±20mm (0.78in) or ±0.04% of measurement range (Whichever is greater)					
Accuracy	Temp. Error	Standard: ± 0.03% /10K, Ex-proof: 0.06%/6K					
Ambient	Housing	Standard: -40 ~ +80°C (-40 ~ +176°F ), With LCD: -20 ~ +60°C (-4 ~ +140°F ), Ex-proof: -20 ~ +50°C (-4 ~ +122°F )  1 hour is required to warm up the device if the temperature is lower than -20°C (-4°F ).					
Temperature							
, i	Antenna			· · · · · · · · · · · · · · · · · · ·	, Ex-proof: -40 ~ +100℃	· · · · · · · · · · · · · · · · · · ·	
Allowable F		1MPa	490kPa	500kPa	1MPa	250kPa	500kPa
Material	Housing	ADC					
	Antenna	SUS316L					
Protection		IP67 (Housing cover and lead outlet must be closed)					
Lead Outlet		1-G1/2 (Applicable cable size: $\phi$ 8 to 12mm (0.31 to 0.47in)  DC4 $\sim$ 20mA $\times$ 1 (Load resistance when 24VDC power supply is used; 499 $\Omega$ max), HART communication					
Output Sigr		DC4	$\sim$ 20mA $ imes$ 1 (Load resist			2 max), HART communi	cation
Integral Time				· -	999s	T	
Mass	_	Approx. 2.3kg	Approx. 4.4kg	Approx. 6.1kg	Approx. 2.7kg	Approx. 5.3kg	Approx. 6.5kg
Explosion-proof		Intrinsically safe construction Ex ia II B T4 X (TIIS)					
constructio							
Division of hazadous	Housing	Zone1, Zone2					
section	Antenna	1.05 "			ne1, Zone2	DO 11 1 1 2	(14.5714)
Accessories	s (option)	,	stment unit (GRAPHIC ( TC4-Ex1) is needed to (	·		,	

\*: Explosion Proof model has Ex written at the end of each model. Explosion proof structure is Ex ia IB T4 (TIIS).

## Dimension mm [in]



## Distributor

Specifications are subject to change without notice.

All Rights Reserved Copyright ©2020, Matsushima Measure Tech Co.,Ltd.

### **HEAD OFFICE**



## Matsushima Measure Tech Co.,Ltd.

HEAD SALES OFFICE / FACTORY
1-8-18, Norimatuhigashi, Yahatanishi-ku, Kitakyushu, 807-0837, Japan
Tel: +81-(0)93-691-3731 Fax: +81-(0)93-691-3735

SHANGHAI DAHONG MATSUSHIMA MACHINERY CO., LTD. 70 Hengcang Road, Dahong, Malu, Jiading, Shanghai 201801, China Tel: +86-(0)21-59514138 Fax: +86-(0)21-59514139

for any systems used in situations which may be life threatening.

### Seoul Liaison Office (Korea)

220, ZF Hyundai Knowledge Industry Center, 70, Dusan-ro, Geumcheon-gu, Seoul, Republic of Korea 08584 Tel: +82-(0)2-852-3731 Fax: +82-(0)2-852-3734