

INSTRUCTION MANUAL

FOR

Dust Monitor

TYPE

PFM-KCU14 (Transducer)

PFM-M11P (Sensor)

PFM-M11PT (High-temperature type)

Contents

1. Outline	2
2. Specification	3
3. Shape	4
4. Mounting method	5
5. How to connect	6, 7
6. Part names and functions	8
7. Start up	9 ~ 11
8. Setup example of Parameter	12
9. Maintenance	12
10. Trouble shooting	13, 14

※The operator should read this Instruction Manual carefully and handle the device correctly.

Matsushima Measure Tech Co.,Ltd.

1-8-18 Norimatsu-Higashi, Yahatanishi-ku, Kitakyushu 807-0837 Japan
Phone No. (8193) 691-3731 Fax No. (8193) 691-3735
<http://www.matsushima-m-tech.com>
E-mail sales@matsushima-m-tech.com

Safety Precautions

- Be sure to thoroughly read the instruction manual before using the products.
- Keep the instruction manual in a safe, convenient location for future reference.
- All or part of the contents described in this manual may be changed without any notice.
- Due to our constant striving for further improvement of products, parts or products that differ from those described in this manual may be substituted.



WARNING (Failure to observe this WARNING may cause a fatal or serious injury.)

- Be sure to confirm that any peripheral equipment does not move before installation work.
In addition, observe safety requirements for installation work where high-place work is expected.
- Be sure to turn off the power source before wiring, mounting and transportation work. (Failure to observe this WARNING may result in an electric shock/ injury or equipment damage due to short-circuit.)
- Carry out wiring work correctly with reference to a proper drawing.
- Never disassemble the equipment. (Failure to observe this WARNING may result in an electric shock.)
- Do not open the cover under an explosive environmental condition when power is entered. (Failure to observe this WARNING may result in an injury or equipment damage.)
- Do not place or store the equipment in any hostile environmental place where it will be subjected to direct sunlight, rain, water droplet, hazardous gas/water, etc..



CAUTION (Failure to observe this CAUTION may cause a moderate injury or equipment damage.)

- Do not use the equipment for any purpose other than the original purpose of use.
- Be sure to confirm the specification of equipment and use the equipment within the range of specification. (Mounting conditions such as temperature, power source, frequency, etc.)
- Make sure a correct wiring before applying power source.
- Do not have a shock or strong impact to the equipment.
(Failure to observe this CAUTION may result in equipment damage.)
- Be sure to connect necessary terminals (grounding, etc.).
- Remove all wiring to the equipment before doing electrical welding work near the equipment.
- Do not forcibly bend or pull the lead wire also do not use unnecessarily long wire.
- Tighten the cover, lead outlet, etc. properly so that dust, rainwater, etc. do not enter inside the equipment.
- Do not use the equipment under a corrosive condition (NH₃, SO₂, Cl₂, etc.).
- Be sure to tighten the cable gland so that outer air does not enter inside the equipment.
- When applying piping connection such as conduit, etc. instead of cable gland, apply putty or equivalents on the cable entry so that outer air does not enter inside the equipment.
- Do not directly touch the probe with hands regardless of power ON or OFF.
If you unavoidably have to touch the probe with hands when installation or maintenance process, be sure to turn OFF the power and use non-conductive gloves such as rubber gloves during the process.
*Touching the probe with hand directly may cause a failure due to static electricity charge in a human body.
- **MAINTENANCE:** When you clean the probe, be sure to turn OFF the power, put on non-conductive gloves such as rubber gloves to clean the probe with moist cloth.*Touching the probe with hand directly may cause a failure due to static electricity charge in a human body.Cleaning the probe with dry cloth may also cause a failure due to friction charge generated between the cloth and probe.



IMPORTANT (indicates notes or information to help customers.)

Limitations of Warranty:

- Warranty period shall be one year from the date of delivery (ex-factory).
- Any damage of any other products that have occurred for use of the equipment is not covered by this warranty. Also any loss induced by failure or malfunction of the equipment is not covered by this warranty.
- Failure or malfunction caused by following are not covered by this warranty:
 - a. Modification or repair by a party other than MATSUSHIMA's authorized personnel, or replacement of parts not recommended by MATSUSHIMA.
 - b. Inadequate storage, installation, use, inspection or maintenance that does not comply with specifications.
 - c. Cause for any peripheral equipment or device.
 - d. Accident beyond control and force majeure (fire, earthquake, flood, riots, etc.).

Lack of instructions to MATSUSHIMA for information or safety requirements that can be predicted only by customers' side.

This warranty conditions do not limit customers' legal right.

Price for the equipment does not include any charge for services such as commissioning, supervising, etc..

1. Outline

Electric charge will generate when a number of corpuscle contained in gas pass through and/or get in touch with probe of dust monitor equipped with duct, plumbing pipe, etc.

The dust monitor amplifies this "Displacement of the charge" with the sensor, and sends the amplified slight signal to the output unit.

This electric signal "Displacement of the charge" is both filtered and amplified and then output instrumentation signal of 4~20mA in proportion to dust amount and contact signal as well.



Important : View for density of dust monitor per Friction Electrification Mechanism

Output value of Friction Electric Charge Mechanic dust monitor will be variable due to various environmental factors such as 「kind of particle」 「particle diameter」 「specific gravity」 「current speed」 through measure principle.

Under a regular environment, however, linear characteristic will not of course vary under that environment.

As to considering density regarding to Dust Monitor of Friction Electric Charge Mechanism, it requires you to consider influence due to variation of particle characteristics as afore mentioned and it does not always meet density specified.

Density indicated on specification is for design development of machinery and is publicized for you customers to use as a guideline in deciding the range.

When you customers decide the range, you please find the range and set it in which alarm level is easy to set strictly from 0—100% signal and becomes pulse signal.

By doing so, you can realize your management of exhaust drift.

If there is a need hereby to execute density management, you are recommended to decide density equivalent to 0 - 100%.


On deciding above, you please investigate density of pulse and you can read signal as density from current signal of machinery by jointly utilizing compensation coefficient, integral function, etc to get the range acquiring signal nearest to actual density of 0—100%.

(The value you can get is compensated and is a relative conversion value but not absolute.)


2. Specification

2-1. Power supply	
2-1-1. Power pressure	AC 110V or 220V -15%/+10% (specify on demand) 50/60Hz
2-1-2. Power consumed	7VA
2-2. Material to measure	Solid particle in gas
2-3. Quality of particle	All kind of solid particle
2-4. Particle size	$\geq 0.3\mu\text{m}$
2-5. Density of particle	$0.1\text{mg}/\text{m}^3 \sim 1000\text{mg}/\text{m}^3$
2-6. Measure principle	Friction electric charge detection method
2-7. Measure condition (process condition)	
2-7-1. Temperature	$\leq 250^\circ\text{C}$ (PFM-M11PT: $\leq 400^\circ\text{C}$)
2-7-2. Pressure	$\leq 200\text{kPa}$
2-7-3. Speed	$\geq 4\text{m}/\text{s}$
2-7-4. Humidity	$\leq 40\text{vol}\%$
2-8. Environmental condition	
2-8-1. Temperature	$-20 \sim 65^\circ\text{C}$ (Transducer: 50°C) ※1
2-8-2. Humidity	$\leq 95\%\text{RH}$ (Condition: State of case sealing up)
2-9. Keeping condition	
2-9-1. Temperature	$-20 \sim 65^\circ\text{C}$
2-9-2. Humidity	$\leq 95\%\text{RH}$
2-10. Output signal	
2-10-1. Current output	DC 4 ~ 20mA (isolated output, load resistance : 500Ω) (max. 23.3mA)
2-10-2. Contact output	Alarm contact output $\times 1$ (250VAC, 2A/30VDC, 2A) Upper limit contact (limit) output $\times 2$ (250VAC, 2A/30VDC, 2A)
2-11. Fitting method	R1 fit screw (1"socket), (option: flange fitting)
2-12. Sensitivity switch	<ul style="list-style-type: none"> • 9 steps switch can do • For each range (sensitive) , 0.1~2.0 double output • compensation can do
2-13. Protection structure	IP65 (cover, in a condition of cable gland tightening) IP20 (Transducer)

※1: The maximum temperature is different according to the measuring range.
(Please refer to the chart.)



PFM-M11P



PFM-M11PT

Fig.1. Graph of temperature and humidity

3. Shape (rough drawing)





Fig.2. Shape (rough drawing)

4. Mounting method

To mount Dust Monitor, 1" -socket is provided with.

Weld the socket onto the pipe. Install the dust monitor so it is horizontal or vertical.

Welding should execute all around the pipe to shut off gas.

4-1. Precaution for mounting

Dust Monitor may mal-function in an environment as listed hereunder.

Mounting Monitor in such environment should be refrained from, please.

- (1) Plumbing pipe to be extremely squeezed or close to a place bending.
- (2) Mounting position within diameter of duct or 1.5 of vertical dimension.
- (3) Near a fan
- (4) Fitting plumbing pipe · short pipe · duct are nonconductive.
- (5) Measure environment and conditions are out of specification.
- (6) In case raising bulk up with short pipe in a place where dusts accumulate between short pipe and probe.
- (7) Place where tip of probe is within 20mm from plumbing pipe.



Important : Wiring of power and signal should be independent, please.
Cap is for transport protection and is not a raincoat.



Attention : · Exclusive cable is transmitting very weak signal.
Cable should be protected with, by all means, steel made electric wire pipe independently so that inductive noise form ambient area does not bother signal.
· Securely close the lead outlet to prevent outside air from entering in the main unit.
Do not remove the accessory Silica gel. (for dehumidification)
· Where using conduit piping and so on instead of cable grand, be sure to apply putty or like at cable entry so that ambient air does not come into the unit.
· Isolate the evaluation unit from the outer noise sources and take any measure against noise if there may be any noise from power supply/signal lines.





Fig. 5. Installation reference figure




Fig. 4. Example) Installation not good



Important :
For installation of Sensor,
Place R1 Attachment screw,
then insert Probe and tighten
M5 bolt and nut on the side of
R1 Attachment screw.

For maintenance, by loosening
bolt and nut, you can pull out
Sensor.

5. How to connect




Fig. 6. Removing cover




Fig. 7. Joining screws of terminal and main block part




Fig. 8. Terminal part

There are Attaching Screw Covers at upper and lower portions of a surface of a Transducer. Please remove the covers with a negative driver or the like.

Please keep the covers which you removed.

Please attach the cover which you kept after wiring.

A terminal block part is joined to a main block part with four points of screws and connectors.


You can see a screw joining to the terminal block part under holes for Transducer attaching when you remove the attaching screw covers.

Please loosen these joining screws of the terminal block part with a Phillips driver.

You can see the terminal block of the Transducer when you remove the main block part from the terminal block part after having loosened these Joining Screws.

When you wire the terminal block of the converter, you must not make any false wiring.

After wiring, please attach the main block part with the procedure the reverse of how to remove the main block part.



※Please earth the terminal FG.

Line-connecting terminal :
Max. 1.5mm²

Fig. 9. Connection



Important : EMC-cable gland is used for Sensor.

Again, when wiring. Figure.10. becomes points of wiring.





Fig. 10. becomes points of wiring.

6. Part names and functions



【for indication】

POWER LED : Light on as power on

FAULT LED : CPU on when abnormal

L1 ON LED : Light on over limit1 set

L2 ON LED : Light on over limit1 set

4 beams indicate LED: detection density will indicate per 0-1000mg/m³ complying with setup.

【for button】

→ : use when changing beam of number/value.

↑ : use when increasing number/value.

MOD : use when switching parameter set mode and measure mode.

Pushing after set change will memorize parameter and return to measure mode.

SELECT :

Use when switching set items.

F-RESET :

Use when setting measure again.

Fig.11. Front panel of Output unit

(1) **RANGE** : measure range (1、2、3、4、5、6、7、8、9) set

(2) **L1 ON** : setON point of limit 1 (set range : 0~100%)

(3) **L1 OFF** : setOFF point of limit 1 (set range : 0~100%)

(4) **L2 ON** : setON point of limit 2 (set range : 0~100%)

(5) **L2 OFF** : setOFF point of limit 2 (set range : 0~100%)

Minimum range of Hysteresis is still 1%.

(6) **INTEGRATION TIME** : Integral time set (set range : 0~30 seconds)

(7) **CORRECTION** : Compensation value set (set range : 0.1~2.0)

7. Start up

7-1. Warm up operation

Dust Monitor requires warm up operation for about 1 hour after switch on.

7-2. Measure range set

After finishing warm up operation, you please set most appropriate measure range. You please set the range at 1 - 4 if the condition in which normal flow speed is regular, filter is correct and measure environment is appropriate.

In case requiring observation of smaller change, you please set the range at 5~9 so that you can observe smaller change.

(In case density is high however, you may get over range.)

	4mA (0%)	20mA (100%)		4mA (0%)	20mA (100%)
Measure range 1	: 0.1	~ 1000mg/m ³	Measure range 6	: 0.1	~ 20mg/m ³
Measure range 2	: 0.1	~ 500mg/m ³	Measure range 7	: 0.1	~ 10mg/m ³
Measure range 3	: 0.1	~ 200mg/m ³	Measure range 8	: 0.1	~ 5mg/m ³
Measure range 4	: 0.1	~ 100mg/m ³	Measure range 9	: 0.1	~ 2mg/m ³
Measure range 5	: 0.1	~ 50mg/m ³			

This range (density) , utilizing 「Talc」 as standard powder, is designed to get 20mA output under an environment of flow speed of 10m/s and the maximum range of 1000mg/m³.

As to other ranges, the maximum value of 20mA of each range is designed to output due to its output linear.

【Reference : Talc】

(Talc) is non organic powder made from ore called Talc being crushed into gray white particle and smooth powder.

Talc, with its chemical name : hydrous magnesium silicate (Mg₃Si₄O₁₀(OH)) containing main ingredient of SiO₂ approx 60%, MgO approx 30% and combined water of 4.88%.

As its physical nature, Talc of true specific gravity 2.7~2.8 is a substance having lowest hardness, superior in heat resistance in addition to chemically stable nature among non organic mineral.

7-3. Integral set

Integration will even off measure signal per time fixed number up to maximum 30 seconds. (optional set)

※ Trouble of filter system will indicate through sudden rise of output signal.

When doing analysis of filter system, set integral at 0 second, please.

By setting integral at 0 second, you can monitor sudden change of dust density.

As measure example, bag filter observation example is indicated for you in Fig.12 in which Dust Monitor is used for 13 lines.

Dust exhaust is indicating its respective amount to transact as 1~6 lines, and 12, 13 lines are low but 7~11 lines pretty high peak.

You can decide when you change filter based on your observation.




Fig.12. Filter observation picture (example)

7-4. Limit set

Limit set can be done 2 different upper limits (alarm) in the range of 4~20mA (signal level 0~100%)

In case signal change gets severe however, chattering might rise often.

In such case you may be recommended to use integral function or delay function at/from higher position (Customers expertise) respectively.

【Limit 1, 2 and action chart of trouble alarm】




Fig.13. Operation chart (upper limit alarm)

Trouble alarm





Fig.14. Operation chart (Trouble alarm)


7-5. Compensation value set

Compensation value can output in a range of 0.1~2.0 (double) as compensation coefficient.

In such case as output is too high or too low for actual density when standard coefficient is 1.0, this function can output nearest density to actual density by multiplying output. Utilizing this function, output can be compensated as shown hereunder.



Compensation value 1.0 trend
For actual density,
detect density outputs high.




Compensation value 0.5 trend
For actual density,
Detect density outputs almost
all alike and understood
compensation is effective.

This function is 0.1 in increments of input in the range of 0.1~2.0 (default is 1.0). If management is only for trend of dust exhaust, you can do without using this function (=set value 1.0). In case management requires the nearest value to actual density, you seize actual density such as counter wash pulse time, etc by manual analysis first and then set counter wash pulse shown by device very much close to value of manual analysis.

8. Set example of parameter

8-1. Flow of parameter set

Parameter should set according to the flow as shown hereunder.



- ※ In case setting up value over input range exceeding specification, setup value of parameter will indicate 「E r r」 on indication L E D, let you know setup value is wrong and do not accept next operation.
- ※ In this case, please change to correct set value again.

8-2. Example of parameter set

Following is a set example to set integral time at 1 5 second.

(Providing that set value was 0 second before change.)

- (1) Push M O D button 1 time move to parameter window and LED (orange).
written Range on the left will light on.
- (2) Push S E L button 5 times LED (orange) lit goes down in turn
and INTEGRATION TIME LED will light.
- (3) By using both → button and ↑ button,
set Indication L E D at 「1 5」.
- (4) Push M O D button 1 time return to measure window and start measure
again at integral 1 5 second.

You operate other parameters with same procedure, please.

In case setting other parameters continuously, at (4) above instead of M O D you push S E L and can perform both setting parameter and moving to plural items at the same time.

Reference : Parameter and light up of corresponding L E D

RANGE	: only RANGE LED light up
L1 ON	: only L1 ON LED light up
L1 OFF	: only L1 OFF LED light up
L2 ON	: only L2 ON LED light up
L2 OFF	: only L2 OFF LED light up
INTEGRATION TIME	: only INTEGRATION TIME LED light up
CORRECTION	: both RANGE LED and CORRECTION LED light up same time

9. Maintenance

Measure probe should regularly be wiped and cleaned with dry rag. You please keep it cleaned once in every 3 months but more often because of changing media or measure environment, you see. When cleaning, you please switch off power. Temperature of pipe may be high and dust monitor might be heated accordingly. Be careful! Or you might get your hands burned.



Caution: The earth line should not be removed even at the maintenance in case it may cause a fault.

10. Trouble shooting

When your device has any problem, please refer to the following particulars and solve it by yourselves first. If the device does not recover to normal after those confirmations listed on the right below have been done, please kindly contact Matsushima.

Table 1. Trouble shooting

Contents	Cause thinkable	Items to confirm
Power LED and Other LEDs are off.	<ul style="list-style-type: none"> • Power is not supplied. • Power specification is changed from the ordered specification. • CPU abnormal. 	<ul style="list-style-type: none"> • Confirm power line is wired to Terminal AC. If not supplied, supply power. • Confirm the voltage on name plate of Transducer is the same as the supplied power. If it is different, return us Transducer, then the power spec. will be changed at out site. • Power OFF, then ON.
Output Direction is unstable.	<ul style="list-style-type: none"> • Warm up operation after setup is not complete. • Grounding is not provided. • The wiring between Sensor and Transducer is either off or wrong. • Material sticking on Probe electrode. • Probe electrode has dew condensation. • A tiny amount of material is flowing. 	<ul style="list-style-type: none"> • Make warm up operation for 1 hour and check output again. • Confirm D class grounding (100ohm or less) is done. • Confirm wiring of exclusive cable. (See Page 6, 5.How to connect.) If wiring is wrong, rewire correctly. • Remove Sensor and check if any sticking on Probe electrode. If yes, power off and wipe them off with moist cloth. (See NOTE) • Remove Sensor and check if Probe electrode has dew condensation. If yes, power off and wipe it off with moist cloth. (See NOTE) • Check if an applicable amount is flowing. If necessary, change the measurement range and integral setting.
Output indication goes off scale and does not recover.	<ul style="list-style-type: none"> • Duct or pipe is short-circuited with Probe electrode due to the sticking material. • Probe electrode has dew condensation. • Probe electrode is in contact with pipe inside (GND). • Device is in trouble. • A large amount of material is flowing. • CPU abnormal. 	<ul style="list-style-type: none"> • Remove Sensor and check if any sticking on Probe electrode. If yes, power off and wipe them off with moist cloth. (See NOTE) • Confirm if Insulation is inserted more than 10mm into Duct or Pipe. Insulation should be extended if necessary. (See NOTE) • Remove Sensor and check if Probe electrode has dew condensation. If yes, power off and wipe it off with moist cloth. (See NOTE) • Measure inside diameter and Probe electrode length and check if they are not in contact. If yes, change electrode length. (See NOTE) • Consult with Sales Dept. to check the soundness of Device. • Check if applicable amount of material is flowing. Shorten Probe electrode if necessary. (See NOTE) • Power OFF, then ON.

Output indication does not change.	<ul style="list-style-type: none"> • Power is not supplied. • The wiring between Sensor and Transducer is either off or wrong. • Material sticking on Probe electrode. • Probe electrode is in contact with pipe inside (GND). • Device is in trouble. • CPU abnormal. 	<ul style="list-style-type: none"> • Confirm power line is wired to Terminal AC. If not supplied, supply power. • Check wiring of exclusive cable. (See Page 6, 5. How to connect.) If wiring is wrong, rewire correctly. • Remove Sensor and check if any sticking on Probe electrode. If yes, power off and wipe them off with moist cloth. (See NOTE) • Measure inside diameter and Probe electrode length and check if they are not in contact. If yes, change electrode length. (See NOTE) • Consult with Sales Dept. to check the soundness of Device. • Power OFF, then ON.
Fault LED is lighted.	<ul style="list-style-type: none"> • Wiring is wrong. • The supplied power supply is out of allowable range. • CPU abnormal. 	<ul style="list-style-type: none"> • Check wiring of power/output signal lines, exclusive cable. (See Page 6, 5. How to connect.) If wiring is wrong, rewire correctly. • Check power supply with a Tester etc.. If it is out of the allowable range, apply the one within the range. • Power OFF, then ON.

[NOTE]

(1) When removing Sensor, loosen M5 bolts and nuts.

Securely tighten them at installation after cleaning it.

(2) If insulation extension is required, consult with Sales Dept. of Matsushima. (non-free)

(3) Do not cut probe length too short in case any electric charge may not be detected.